


# **Mercury switchProduct Details specification**



Add: Suwu Industrial Zone,Bajiaowo Village,Wangjiang District,Dongguan, Guangdong TEL: 86+769+22176561 Fax: 86+769+22778617 Http://www.blswitch.com E-mail:dgbailin@126.com



# **Mercury switchProduct Details specification**

Model	Appearance Image	Electrical characteristics	Installation Style	SIZE Unit=mm
2001	Beelee SW-2001	1A 220V	terminal more than 7° is open Angle, is closed	© 9.5 <sup>*0.1</sup>
2001A	Beelee SW-2001A	2A 220V	terminal more than Trigger below 7° 7° is open Angle, is closed	Ф 1.0 3.3 <sup>+0.1</sup> Ф 1.0 Ф 1
2002	Beelee SW-2002	2A 220V	terminal more than Trigger below10° 10° is open Angle, is closed	Ф12.2 <sup>40.1</sup> 43.0 <sup>+1</sup>
2004	Beelee sw-2004	2A 220V	level place is ON	Φ10.5 <sup>-0.1</sup> 35.0 <sup>+0.4</sup> 4.5 →
2012	Booloo sw-2012	2A 220V	terminal more than Trigger below10° 10° is open Angle, is closed	Φ12.0 <sup>+0.1</sup> 45.0 <sup>+1</sup>

Add: Suwu Industrial Zone,Bajiaowo Village,Wangjiang District,Dongguan, Guangdong TEL: 86+769+22176561 Fax: 86+769+22778617 Http://www.blswitch.com E-mail:dgbailin@126.com



## **Mercury switchProduct Details specification**

### Electronic Feature :

1	Voltage:	
2	Current:	
3	Conductive time	Steady
4	Closed resistance	<10 ohm
5	Open resistance	>10M ohm

## Mechanical characteristics:

1	Temperature range:	-40°C to 80°C
2	Pull force of terminal:	500gf for 1 minute
3	Humidity:	95% RH, 40°C for 96 hours
4	Operating lifespan:	500,000 cycles

### Material list:

1	Glass tube	
2	Guide pin Tin plate	
3	Mercury roll ball	
4		
5		

## Welding characteristics

Solder tin, tin content 100% Welding Temperature: 300°C Welding time: 2-2.5 seconds Do not use strong acid, alkali flux

#### Notice :

1.If the products used in the high safety products and the durability of the high of equipment (such as life safety equipment, Aviation, disaster, prevention equipment) pls confirm this product whether is ok for you Or inquiry our company. 2.Pls Not allow overload, in case of fire.

3. The weld temperature and time more than standard, can be cause switch collapse.

4.Do not used water solubility ,can cause damage to the switch.

5.Do not used the solvent to wash the switch.

Add: Suwu Industrial Zone, Bajiaowo Village, Wangjiang District, Dongguan, Guangdong TEL: 86+769+22176561 Fax: 86+769+22778617 Http://www.blswitch.com E-mail:dgbailin@126.com